



## E3JK-RR11 2M

Fotocélula 50x50 Multialim. Espejo 7m Relé Cable 2m LITE

# Especificaciones

<b>Shape</b>	Cuboid
<b>Sensing method</b>	Retro-reflective
<b>Sensing distance</b>	11000 mm
<b>Sensing distance (min.)</b>	100 mm
<b>Setting method</b>	Manual adjustment
<b>Connection method</b>	Cable
<b>Cable length</b>	2 m
<b>Output type</b>	Relay
<b>Operation mode</b>	Dark-ON, Light-ON
<b>Response time</b>	20 ms
<b>Material housing</b>	ABS
<b>Thread size</b>	Other
<b>Width</b>	18 mm
<b>Height</b>	52 mm
<b>Depth</b>	50 mm
<b>Type of light</b>	Polarity free red light
<b>Power supply voltage</b>	24-240 V
<b>Features</b>	Without M.S.R.

# Accesorios



E39-L40

Soporte de montaje E3JK y F3C-AL



E39-R1S

Espejo 60x40mm



E39-R2

Espejo 60x80mm

# Descargas

Librería CAD



**E3JK Built-in Power  
Supply Photoelectric  
Sensor**

**Datasheet**

ES PDF 600 KB

## TÉRMINOS DE USO DEL SITIO WEB

Este documento PDF se generó a partir del sitio web europeo de OMRON Industrial Automation el 7 July, 2022. Haga clic aquí para acceder a los [legal](#).

**OMRON**

INDUSTRIAL AUTOMATION | INDUSTRIAL.OMRON.EU