



E6B2-CWZ1X 360P/R 0.5M

Encoder, incremental, 360ppr, 5 VDC, Line driver 0.5m cable

Especificaciones

Model	Incremental encoder
Construction size	40 mm
Pulses per rotation	360
Signal outputs	A, B, Z
Shaft diameter	6 mm
Power supply voltage	4.8-5.2 V
Output type	Line driver (RS-422)
Connection method	Cable
Cable length	0.5 m

Accesorios



E69-C06B

Acoplamiento encoder D6mm



E69-C06M

Acoplamiento encoder Metálico D6mm



E69-C610B

Acoplamiento encoder D6-D10mm



E69-C68B

Acoplamiento encoder D6-D8mm

Librería CAD



E6B2-C Incremental Rotary Encoder 40 mm Datasheet

ES PDF 300 KB